

# sensio



## FEATURES



Certification  
UL

- Can be used with 12V & 24V LED products
- Delay between 10 seconds and 3 minutes can be set
- 8' detection range
- Can be surface recessed into the back or side of cabinet
- Plug and play, and no additional wiring is required

## SA40521

**LED 12V/24V IR Motion Sensor Switch** - The Motion Sensor IR Light Switch detects motion up to 8 feet away to turn lights on. A dial on the unit allows you to select the time delay for the sensor. The delay can be set for between 10 seconds and 3 minutes. When used inside a cabinet, the switch will turn lights on when the door is opened and turn them off once the preset time delay has elapsed. This sensor can be recessed into the back or side panel of a cabinet so that it is hidden out of sight.

## SPECIFICATIONS

Product Code	Voltage	Hole Cut	Length	Width	Depth	Sensor Diameter
SA40521	12V/24V	0.79" (20mm)	3.39" (86mm)	1.58" (40mm)	0.59" (15mm)	.96" (24.3mm)