


ARBORS

ARBORS

THREADED SHANK TO MORSE TAPER




AO No.	Part No.	Description	Dimensions				Weight Ea. oz
			Overall Length (L)		Threaded Extension		
			in	mm	in	mm	
A0261	7345	2 Morse 3/8" - 24	3.69	93.7	0.56	14.3	4
A0264	7346	2 Morse 1/2" - 20	4.06	103.2	0.56	14.3	5
A0268	7347	2 Morse 5/8" - 16	4.19	106.4	0.69	17.5	5



BRIDGEPORT® TAPER TO JACOBS® TAPER



AO No.	Part No.	Mount Jacobs	Dimensions								Weight Ea. oz				
			Overall Length (L)				Length (C)					Diameter (D)			
			Minimum		Maximum		Minimum		Maximum			Minimum		Maximum	
			in	mm	in	mm	in	mm	in	mm		in	mm	in	mm
A0802	7339	2JT	5.18	131.6	5.20	132.2	0.91	23.0	0.92	23.4	0.49	12.4	0.56	14.2	16
A0803	7340	3JT	5.53	140.4	5.55	140.9	1.25	31.8	1.27	32.1	0.75	18.9	0.81	20.6	17
A0804	7341	4JT	5.97	151.6	5.98	151.8	1.69	42.9	1.70	43.2	1.04	26.3	1.12	28.6	17
A0806	7342	6JT	5.31	134.8	5.33	135.4	1.03	26.2	1.05	26.6	0.62	15.8	0.68	17.2	16
A0833	7343	33JT	5.31	134.8	5.33	135.4	1.03	26.2	1.05	26.6	0.56	14.2	0.62	15.9	16



HOW TO ORDER ARBORS

When ordering arbors

Either of the following is correct:

1. Show the style and size of the mounting shank and the model number of the Jacobs® chuck to which the arbor will be fitted.

Example: A #2 Morse taper shank arbor for a #34 Jacobs® chuck

2. Show the style and size of the mounting shank plus the actual Jacobs® taper desired.

Example: A #2 Morse taper shank with a #3 Jacobs® taper.

MOTOR SHAFT ADAPTER



- Adapts No. 2 Jacobs® taper to 1/2" diameter motor shaft.

Model No.	Part No.	Motor Shaft Size	Jacobs Taper
AD2502	7374	1/2" Dia.	2JT